

ALCS Handset user instructions



Operating instructions

Switch on unit by pressing ON button

To zero unit press ZERO button

To switch off unit, press and hold ZERO button

To change batteries, unclip the plastic cover on the back of the handset, remove old batteries and replace with new 1.5V cells (care being taken on polarity + and – shown on holder case)

To change unit type

To change the unit type, (have the handset already on)

Press the (PAGE) button

Handset will read (UNITS)

Now press the (ON) button

Handset will now read a (UNIT TYPE)

Press the (PAGE) button until, you have the unit type that you require.

Now press the (ON) button to accept, and handset will go back to reading in unit type that you requested.

Peak hold

To use Peak hold,

Press the (PAGE) button 5 times, unit will display Peak hold, press enter key unit will; show off, press (PAGE) button unit will show on, press enter the display is now in peak hold, unit will stay in peak hold until it is switched off by going through set up again.